



Your supplier for RF/microwave components

Bias Tee 300 KHz-110 GHz



Broadband Bias Tee Model # AT-BTL-110L1

Frequency Range: 300 KHz-110GHz

Insertion Loss: 10MHz-90GHz: -2.5dB typ.

90-110GHz: -4.0dB typ.

Return Loss: -10dB

Group Delay: 100ps

Max Voltage: +25V

Current: 250mA

Power Handling: +27dBm max.

Connectors

RF+DC Port: 1.0mm male

RF Port: 1mm female

DC Port: SMA-female

Low cost, fast lead times

www.bq-microwave.de

www.bq-microwave.de

Tel: +49 151 25290128

Email: info@bq-microwave.de